

F5 Push Button Switch Operation

- **Switching programs**
Tap the right or left button to change programs.
The decimal point will light up and the chip will not actually switch to the next program until it goes out. You can delay changing to the next position by holding the button down. Release the button to start the switching timer.
- **Position 0 operation**
 - **Accessing position 0**
Press both buttons while the key is on. The chip will not change to position 0 while the key is on. The display will blink on position 0 and it does not go to that position until the key is turned off. The display will not light when the key is turned on while in position 0.
 - **Exiting position 0**
Turn the ignition on. Press and hold the left button for 3 seconds to exit. The switch will return to position 1.
- **Contrast control**
Press both buttons and while the 0 is blinking press the left button. The display will display C. Push the right button to set the contrast level. Push the left button to save and exit. The switch will return to position 1.